

## PC1013BII PA Partitioner



### Features

- 2-channel inputs (A and B), 10-channel output to control 10 zones.
- 2 input alarm levels available (0V and 5V-24V).
- Emergency broadcast override function (The short-circuit signal is preferentially switched to the emergency broadcast channel).
- Clear alarm indicator and output signal indicator.
- Support PC remote control.

### Specification

Number of Channels	10, can be selected at will
Input Capacity	70V-100V, 10A (power input)
Output Capacity	Each channel 70V-100V, 5A (power output)
Alarm Signal	+5V-24V, 0V (short circuit) can be preset
Protection	AC fuse
Power	AC 220V/ 50Hz
Package Dimensions (mm)	(L×W×H) 555×455×185
Machine Dimensions (mm)	(L×W×H) 484×320×88
Gross Weight	8kg
Net Weight	6.2kg